


**VM15B4 VA**

15.6" WXGA High Brightness Color TFT-LCD Module

FEATURES	
	- 1366 x768 resolution
	- 2500nits Extreme high brightness
	- Normally white
	- 160/160 view angle
	- 10ms response time
	- LVDS interface
	- -20~70C Wide operation temperature
	- 80K Hrs backlight operation lifetime
	- RoHS Compliance

## Display Specifications

Items	Unit	Specification
Screen Diagonal	inch	15.6
Active Area	mm	344.232(H) x193.536(V)
Pixels H x V	pixels	1366(x3) x 768
Pixels Pitch	um	252 (per one triad) x 252
Pixel Arrangement		RGB Vertical stripe
Display mode		TN mode, normally white
White luminance (center)	Cd/m <sup>2</sup>	2500 (typ.)
Contrast ratio		500 (Typ.)
Optical Response Time	msec	10 ms (Typ. on/off)
Normal Input Voltage VDD	Volt	5
Power Consumption (Vcc Line + LED Line)	Watt	24.75 W (Typ) Vcc=1.35 W LED=23.4W
Weight	Grams	1190 (max)
Physical size	mm	363.8(W) x 215.92(H) (Typ) x 16.65(D) (Max)
Electrical Interface		One Channel LVDS
Support Colors		262K / 16.7 M colors
Color Gamut		65% NTSC
Surface Treatment		Anti-Glare, 3H
Temperature range		
Operating	°C	-20 ~ 70 (TFT surface temperature)
Storage (Shipping)	°C	-20 ~ 70
RoHS Compliance		RoHS Compliance

Note: This specification is subject to change without notice.

## ● Accessories for option:

## &gt;&gt; Industrial grade Signal control board &amp; SoC

Input	Output	Resolution
RGB with voltage integration	RGB	TBD
LVDS with voltage & backlight driver integration	RGB	WXGA (max)
LVDS with voltage & backlight driver integration	LVDS	WXGA (max)
VGA/DVI/DP...etc.	RGB/ LVDS / mipi / eDP / V-by-One	4K (max.)
ARM Cortex A17/A53 (Android 6, 8, & 11)	LVDS / eDP / V-by-One	4K (max.)

## &gt;&gt; Industrial grade LED driver board:

Input	Max Output	Dimming control
12V DC	36V *1 port	PWM
12~24V DC	53V * 1 port	PWM / Analog
12~24V DC	53V * 2 port	PWM / Analog
24V	120V / 150V * 1/2 port	PWM

## &gt;&gt; Industrial grade interactive interface:

Type	Input	Output	Protection glass thickness
Projected capacitive touch panel	Fingers / stylus	USB / i2C	Max 6mm
4wire / 5 wire resistance touch panel	Fingers / stylus	USB / RS232	TBD
Option: 1. Customized cover glass design, special color printing 2. AG/AR/AF Surface treatment, 3. Lamination process, 4. Gloved touch function design, 5. Waterproof touch function design 6. EMI shielding touch design			

- HANDLING PRECAUTIONS

- 1) Since front polarizer is easily damaged, pay attention not to scratch it.
- 2) Be sure to turn off power supply when inserting or disconnecting from input connector.
- 3) Wipe off water drop immediately. Long contact with water may cause discoloration or spots.
- 4) When the panel surface is soiled, wipe it with absorbent cotton or other soft cloth.
- 5) Since the panel is made of glass, it may break or crack if dropped or bumped on hard surface.
- 6) Since CMOS LSI is used in this module, take care of static electricity and insure human earth when handling.
- 7) Do not open or modify the Module Assembly.
- 8) Do not press the reflector sheet at the back of the module to any directions.
- 9) In case if a Module has to be put back into the packing container slot after once it was taken out from the container, do not press the center of TFTLCD panel.
- 10) At the insertion or removal of the Signal Interface Connector, be sure not to rotate nor tilt the Interface Connector of the TFT Module.
- 11) After installation of the TFT Module into an enclosure, do not twist nor bend the TFT Module even momentary. At designing the enclosure, it should be taken into consideration that no bending/twisting forces are applied to the TFT Module from outside. Otherwise the TFT Module may be damaged.